

NON-CONTACT AC VOLTAGE DETECTOR



EGA Master has developed a wide range of high precision and innovative electronic measuring and testing instruments, that will help professional end-users to do their job with complete safety, certain of a well done job.





C € *G12

Conforms to the following standards EN61010-1, UL61010-1 and N° 61010-1 CASC 22.1



1. Non-contact AC voltage detector has been designed to test the existence of alternating current, warning the user by the emission of a sound and a LED blinking.

NON-CONTACT AC VOLTAGE DETECTOR



| COD | |
|-------|----|
| 51256 | 75 |

| 1 | |
|---|--|

TECHNICAL SPECIFICATIONS

| ACV | 90-1000V |
|-----------|--------------|
| Hz | 50/60Hz |
| Indicator | Beep & LED |
| Auto off | 30 mins |
| Power | 3V (2 x AAA) |

*G12: 12 MONTHS OF WARRANTY

**Devices for any type of measurements, such as electric, electronic, insulation, illumination, temperature, sound or speed...for the most demanding industrial sectors and professionals: Automotive, Aeronautics, Illumination, Electric, Electronic, Industrial Maintenance, Health & Safety, Construction, Railway, Shipbuilding and a long etc.